









## DEUTZ Diesel Engine

### Technical Data

Engine Model	DEUTZ TBD226B-6
Number of Cylinders	6
Cylinder arrangement	Vertical in-line
Cycle	Four stroke
Aspiration	Turbocharged Air-Air Aftercooled
Bore×Stroke (mm×mm)	105*130
Displacement (Liter)	6.75
Compression Ratio	16:01
Prime Power/Speed (kW/rpm)	80/1500RPM
Standby Power/Speed (kW/rpm)	88/1500RPM
Speed Governor	Electronic
Cooling System	Water-cooled, 50°C radiator is standard
Speed Stability (%)	≤1%
Total lubrication system capacity (L)	50
Coolant capacity (without radiator) (L)	30
Fuel Consumption at 100% Load (L/H)	31,8
Starter Motor	DC24V
Start type	Electrical

## Stamford Alternator (Standard)

### Technical Data

Alternator Model	SGR-110
Exciter type	Brushless, Self-excited
Power factor	0.8
Voltage Adjust range	≥5%
Voltage Regulation NL-FL	≤±0.5%
Insulation Grade	H
Protection Grade	IP23

# Control System

1. Standard: Deepsea DSE7320 AMF Digital Controller
2. Standart: Datakom DKG309

Providing the standard functions as follows:

(Also can be made according to the customers' special requirements)

- \* Automatic Start/Stop
- \* Settings can be adjustable via key buttons on front panel
- \* 3 start attempts failure and Automatic Crank Disconnect
- \* Parameters display (V/A/Hz/Hour)
- \* Engine monitoring and protection
- \* Charge alter nator exciting and Charge alternator fail alarm
- \* Running hour counting
- \* Emergency stop pushbutton
- \* Alarm System: Over speed, High Engine Temperature Low Oil Pressure, Charge Fail
- \* Protection System: Over speed, High Engine Temperature, Low Oil Pressure , Emergency Stop. And the other protection function pre-setting

Digital Auto-start Generator controller integrating digital, intelligent and network techniques is used for automatic control system of diese l generator. It can carry out functions including automatic start/stop, data measure and alarming. Optionally assembled with the ATS, it can carry out auto-switching between the outer power and generating set power. (AMF)

2. Option: Harsen GU641B AMF Digital Auto Start
3. Option: ComAp AMF25 Digital Auto Start
4. Option: Deepsea DSE3110 Digital Auto Start



(1) DSE7320



(2) GU641B



(3) AMF25



(4) DSE3110